

# SNL/CA Manual Dialing

## Manual Dialing a Call

There are different ways to do a manual call in the rooms:

Type	Prefix
FTS Internal ISDN	144
FTS External ISDN	141
Commercial	142

Examples:

Standard (SNL/NM only)      8441234      goes over SNL PRI lines (least expensive)  
 FTS 2001 call                      1448441234      only to other FTS capable sites  
 Commercial call      14215058441234\*      To any site (Most expensive)

\*NOTE: commercial calls are the only one to require the 1 before the 10 digit phone number.

Some videoconferencing equipment have separate external IMUX which require additional dialing codes. Dialing codes tell the equipment the speed of the call and whether the call is FTS or PacBell. Most rooms have documentation describing the type of equipment used. Only the PictureTel Concorde 4X00 series and the Swiftsite series require the use of dialing codes.

The tables on the following page are provided for those units.

### PROMPTUS IMUX:

#1*	"A" Channel	2x56
#2*	"B" Channel	
#6*	"A" Channel	2x64
#7*	"B" Channel	
#3*	Dial on "A" Channel Only	128K
#4*	Dial on "A" Channel Only	256K
#8*	Dial on "A" Channel Only	336K
#5*	Dial on "A" Channel Only	384K

\*\*\* Dialing code string goes **before** phone number \*\*\*

### ASCEND IMUX:

#003	"A" Channel	2x56
#003	"B" Channel	
#004	"A" Channel	2x64
#004	"B" Channel	
#005	Dial on "A" Channel Only	336K
#006	Dial on "A" Channel Only	384K

\*\*\* Dialing code string goes **before** phone number \*\*\*

**Sandia Direct Line:** 1438455555 (use for all Sandia/NM calls)  
**FTS2001:** 1448452222 (may use for Sandia/NM calls)  
**FTS2000:** 1415058452222  
**PacBell:** 14213019035555 (use for all commercial numbers)